


ORDER #:



Specifications

GENERAL DESCRIPTION

The Utility Postop LED is designed for ease of maintenance with the plug-in driver module common to each of the luminaires in Holophane's Utility Luminaire Series. A precision optical system maximizes post spacings while maintaining uniform illumination.

OPTICAL SYSTEM

The optical system consists of a precisely engineered LED circuit board located in the top cover. A gasket between the cover and ring along with a flat glass plate and gasket beneath the reflector create a sealed optical compartment that meets an IP rating. Optics designed to provide an I.E.S. Asymmetric or Symmetric full cutoff distribution are available.

LUMINAIRE HOUSING

The luminaire housing, cast of aluminum, anchors the optical system and provides an enclosure for the plug in electrical module. The electrical enclosure conforms to an IP55 rating. For use with units with an E.E.I.-N.E.M.A. twist lock photocell receptacle, the housing contains a glass "window" to allow light to reach the cell. The nickel plated lamp grip socket and the three station incoming line terminal block are pre-wired to a five conductor receptacle for ease in connecting the electrical module. A slipfitter will accept a 3" high by 2 7/8" to 3 1/8" O.D. pole tenon.

LUMINAIRE HOUSING DOOR

Cast of aluminum, the housing door is hinged and latched to the housing. The door forms the mount for the electrical module, and allows easy access during maintenance.

ELECTRICAL MODULE

The electrical components are mounted to an aluminum plate that is removable with standard tools. A matching five plug connector connects the electrical components to the surge protector for quick replacement. For Photoelectric operation, the electrical module is provided with an E.E.I.-N.E.M.A. twist lock Photocell receptacle.

TOP COVER

The top cover, cast of aluminum, is attached to the top ring of the luminaire housing by a stainless steel hinge pin. The cover is latched by an overcenter, positive action, stainless steel latch which allows tool-less entry to the lamp chamber for relamping.

DRIVER

Voltage sensing 120-277V or 347-480V, 50/60 Hz electronic drivers are >90% efficient. Potted for increased thermal management. Removable through hinged door housing. Available with 0-10V dimming control signal input. Refer to Driver Data Sheet for specific operating characteristics.

FINISH

The luminaire is finished with polyester powder paint applied to ensure maximum durability.

UL

The luminaire is UL listed as suitable for wet locations at a maximum of 40 degrees C ambient temperature.



Architectural Outdoor





PROVED SHALL BECOMETER

SOVER, AND TOS BETANISHED BY HOLOPHANE

BOYER, AND TOS BINLANDED BY HOLOPHANE

RS AN ANCHOR BOLT TEMPALE THE PAIR

MACHOR BOLT TEMPALE THE PAIR

THE ROCERTY OF HOLOPHANE AND IS

ONE HOROPHANE AND IS

ONE HOLOPHANE AND IS

ONE BOLD SHARP TO HOLOPHANE AND IS

ONE HOLOPHANE AND IS

ONE BOLD SHARP TO HOLOPHANE AND IS

ONE BOLD SHARP THE THE PAIR

ONE BOLD SHARP THE PAIR

ON THIS DRAWING, M
SPECIFICATION FO
ON THE ORDER N
SUPPLIED, BUTO
BE SUPPLIED WIT
PROVIDED. THIS
LOANED SUBJEC
CONDITION THA
ANY WAY DETRIIL
CONNECTION WIT

RXXXY² = Receptacle provision.

SXXXY2 = Small provision.


FGB = GFI receptacle in base


Α¥ 10/3/13 POL

KRW DRAWN: DATE IYPE DWG

#

ORDER





DESCRIPTION

The lighting post shall be all aluminum, one-piece construction, with a classic tapered and fluted base design.

The base shall be heavy wall, cast aluminum produced from certified ASTM 356.1 ingot per ASTM B-179-95a or ASTM B26-95. The straight shafts shall be extruded from aluminum, ASTM 6061 alloy, heat treated to a T6 temper. The tapered shaft shall be extruded from aluminum, ASTM 6063 alloy, spun to a tapered shape, then heat treated to a T6 temper. All hardware shall be tamper resistant stainless steel. Anchor bolts to be completely hot dip galvanized.

Accessories WDA17BRKWYKITXX = BREAKAWAY KIT

CONSTRUCTION

The shaft shall be double welded to the base casting and shipped as one piece for maximum structural integrity. The shaft shall be welded inside the base casting at the top of the access door, and externally where the shaft exits the base. All welding shall be per ANSI/AWS


DIMENSIONS


The post shall be X'- XX" in height with a 17" or 20" diameter base. The shaft diameter shall be XX". At the top of the post, an integral tenon with a transitional donut shall be provided for luminaire mounting.

The post shall be provided with four, hot dip galvanized L-type anchor bolts. A door shall be provided in the base for anchorage and wiring access. A grounding screw shall be provided inside the base opposite the door.


² - Replace "XXX" with height from grade (inches), can be up to 3 digits. Must use whole numbers. Leading zeros are not used. Replace Y with orientation from hand hole (A=0, B=90, C=180, D=270). Add multiple provisions as necessary to cover each location. Must validate EPA restrictions for banners.


ANCHORAGE GUIDE






FOR USE WITH CONCRETE BASE





NOTE:

CONCRETE BASE AND/OR HELICAL BASE DESIGN REQUIRED FOR EACH PROJECT LOCATION BASED JPON SITE CONDITIONS.



(4 per Post)

NORTH YORKSHI **Aluminum Pole**

Architectural Outdoor



POL NYA 10/3/13 KRW ORDER #:

DRAWN:

